

This guide will help you configure your router step by step using web management.









Step One

- Firstly, ensure a live and connected SIM card is inserted into the rear of the modem. The TP Link Archer MR600 requires a Micro SIM.
- Power the device on, with the power lead connected, and the Wi-Fi logo light clearly displayed on the router.
- On a laptop/computer, click on the Wi-Fi connections and the TP Link should be displayed on the list, as per **Diagram 1**:
- Ensure you connect to the TP Link router by using the Network Password found on the base of the router on the white sticker.
- Go onto your preferred internet browser window (such as Google Chrome, Microsoft Edge or Apple Safari) and launch the web page <u>http://tplinkmodem.net</u>
- Create a new password for your TP Link login and click 'next'.

~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~	Daisy Group VPN						
~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~	Daisy VPN - Split Tunnel Connected						
(h.	SKYDCCDZ Connected, secured						
(i.	TP-Link_7981 Secured Connect automatically Connect						
(h.	TP-Link_7981_5G Secured						
Network & Internet settings Change settings, such as making a connection metered.							
<i>lia</i> Wi-Fi	ကို (၇) Mobile Airplane mode hotspot						

DIAGRAM 1 - WI-FI CONNECTIONS

Step Two

• Then select a Time Zone as per Diagram 2 and click 'next'.

5	× 🖓 Archer MR600	× +						0	- ø ×
← → C Ô ▲ No	ot secure tplinkmodem.net								☆ 🔕 i
🔢 Apps 💿 Google Hangou	ts 💽 Intouch 🕎 FLIP 🚊 ANVIL	🔄 Cirrus 🔝 Horizo	n						Reading list
	Ptp-link	Quick Setup	Basic	Advanced	English	<mark>→</mark> (3)	}¦⊱ set Rebos		
		SIM		Connection Test	3	P-Link Cloud Service			
					•				
	Time Zone		Wireless Settings		Summary				
	Select yo	ur Time Zone.							
	Time Zon	e: (GMT)	Greenwich Mean Time	Dublin, Edinburgh, Lor	idon, Lisbon	v			
					EXIT	NEX			
	Firmware Version: 1.2.0 0.9.1 v0001.0 Bu	ld 200511 Rel 44954n	Hardware Version An	cher MR500 v1 00000001	IME1:86537104195476	3	Support Aq	2	
DIAGRAM 2 - SELECTING TI	MF ZONES								



Step Three

• On the next screen the customer will need to create a new data profile for the network SIM placed in the handset. This will be is either O2 or Vodafone. To do this you will need to click on 'Advanced – Network – Internet' and select 'Create Profile' which is found at the bottom.

	•						
-	P tp-link	Quick Setup Basic	Advanced	English 🗸	Eog out	옷 Rebot	
(Q Search	NAL:					
	Network	Network Mode: Dial-up Settings	4G Preferred	¥		0	
	- Internet	Network Search:	Auto	¥			
	- ISP Upgrade	Profile Name: PDP Type:	O2(default:1)	*			
	- PIN Management	APN:	m-bb.o2.co.uk				
	- Data Settings	Username:	vertigo				
	- LAN Settings	Password: Authentication Type:	CHAP	ø			
	- Dynamic DNS						
1	- Static Routing	Create Profile Click this button to	o create a new dial-up profile. Up to t	8 profiles can be added.			
	- IPv6 Tunnel			De	iete Save		





Step Four

Creating Profiles

Please ensure the correct profile settings are used, based upon the product purchased.

The profile settings needed are as follows:

Vodafone	
----------	--

APN:

PDP Type:

Profile Name: Vodafoneinternet

wap.vodafone.co.uk

IPv4

APN Type: Dynamic

Username: wap

Password: wap

Authentication Type: None

0	× 🖓 Archer MR600	× +			o - ø ×
	ot secure tplinkmodem.net				🖈 🔕 :
Apps 🔍 Google Hangou	its 💽 Intouch 📴 FLIP 🖳 ANVIL	🚰 Cirrus 🔛 Horizon			Reading list
			- Contraction	. 2 *	
		Quick Setup Basic	Advanced	Log out Reboot	
	Q Search			0	
	Network	Network Mode.	4G Preterred	Ø	
	- Hourson	Dial-up Settings			
	- Internet	Network Search:	Auto 👻		
	1969/2018/	Profile Name:	O2(default:1)		1
	- ISP Upgrade	PDP Type:	IPv4 🖤		
	- PIN Management	APN:	m-bb.o2.co.uk		
	- Data Settings	Username:	vertigo		
		Password:	ø		
	- LAN Settings	Authentication Type:	CHAP.		
	- Dynamic DNS				
- - -	- Static Routing	Create Profile Click this button to create	eate a new dial-up profile. Up to 8 profiles can be	added.	
	- IPv6 Tunnel			Delete Save	
	Firmware Version 1.2.0 0.9.1 v0001.0 B	ulld 200511 Rel.44954n Hardware Version:J	Archer MR600 v1 00000001 IMEI:8653710419	54768 <u>Support</u> Ang	

DIAGRAM 4 - PROFILE SETTINGS

Step Five

- Save the changes and the icons will then light up on the router to indicate the 4G+ and internet connection has been established as per Diagram 5.
- Test the internet connection by doing an internet search to ensure web pages open up correctly.





